Flexem Flexem □□ Series Service Manual

FR-A0400M

1. Description

Flexem FR-A0400M □□□□□□□ 4□□□□□□□□16□□□□□0~10V□0~20mA

3. Product Information

Flexem FR-A0400M □□□□□□□ 4□□□□□□□□16□□□□□0~10V□0~20mA

FEATURES FR-A0400M

Input 4

Output /

Resolution 16 bit

Input/Output Signa Voltage-10V~10V;Current 0~20mA

Full Range Value Customized(-30000~30000)

Conversion Precesion

(Full Scale Range) ±0.2%

Maximum Input Signal allowed Voltage:30V;Current30mA

Imoedence Input Voltage>200K ohms;Current<250 ohms+5%

Wiring Strucutre Removable terminal block

Working Temperature -10~60℃

Storage Temperature -20~70℃

Environment Humidity 5%~95%RH(Non-condensing)

Dimension 111mm×18mm×76 mm

Weight 65g

www.autronexa.com