Flexem Flexem □□ Series Service Manual

F5-BA0101B

1. Description

Flexem F5-Ba0101b Analog Expansion Board

3. Product Information

Flexem F5-Ba0101b Analog Expansion Board

Input 1

Output 1

Resolution 12-bit

Input/Output Signal Range Voltage:0-10V;Current 0-20mA/4-20mA

FullRange Customized (0~4096)

Conversion Precision

(full range) ±1%

Maximum Signal Input Voltage:30v;Current :30mA

Impedance Input Voltage>100k ohms Current<250ohms+5%

Output Load Range Voltage>2k ohms Current<500ohms

Power Supply 5VDC-15%/+20%, 3.2W max. The main unit is provided internally without external input

Wiring Structure Non-removable terminal block

Working Temperature -10~60ºC

Storage Temperature -20~70ºC

Environment Humidity 5%~95%RH(Non-condensing)

Installation CPU Front expansion board slot

Dimension 38mmx40mmx18mm

www.autronexa.com