Flexem Flexem □□ Series Service Manual

F5-MA0400A

1. Description

Flexem F5-MA0400A 4 Input, 16bit Resolution Expansion Module

3. Product Information

Flexem F5-MA0400A 4 Input, 16bit Resolution Expansion Module

Input 4

Output /

Resolution 16-bit

Input/Output Signa Input: Voltage-10V~10V, Current 0~20mA

output: Voltage 0V~10V, Current 0~20mA

Full Range Value Customized (-30000~30000)

Conversion Precesion

(Full Scale Range) ±0.2%

Maximum Input Signal

allowed Voltage:30V

Current:30mA

Imoedence Input Voltage>200Kohms

Current<250ohms+5%

Output load Range Allowed /

Power Rupply 24VDC-15%/+20%,3.2W max.The main unit is provided internally without external input

Wiring Strucutre Removable terminal block

Working Temperature -10~60ºC

Storage Temperature -20~70ºC

Environment Humidity 5%~95%RH (Non-condensing)

Installaton Directly installed on DIN46277 (35mm width)guide rail or fixed with screws

Dimension Dimension A

www.autronexa.com