Flexem Flexem □□ Series Service Manual

F5-MD0016R

1. Description

Flexem F5-MD0016R 6 Output Digital Expansion Module

3. Product Information

Flexem F5-MD0016R 6 Output Digital Expansion Module

Output Characterstics 16 Point

Rated Voltage 24VDC,220VAC

Input Range 5V~30VDC;100VAC~250VAC

Rated Current Maximum2A/point

Current/group (4 points) 4A(relay output @60ºC,50%derating required)

Maximum Switch Voltage 250VAC,30VDC

Current/point 5A

Isolation Type Relay coil

Maximum Load 0.1Hz

Without Load 5Hz

Resistive Load 2A/point/24VDC/220VAC

Mechanical Life Minimum:5,000,000 times

Electrical Contact Life Minimum:100,000 times

Short Circuit Protection None

Wiring Structure Removable terminal block

Dimension Dimension B

www.autronexa.com